

LED G80/G95 Dimmable Opal Globe




Energy saving LED 80/95mm Globe shaped replacement lamp featuring dimmable LED technology and opal white coloured glass to closely resemble the look and feel of a traditional globe lamp.

- 15,000 hour life
- 7,500 switching cycles
- 2700K warm white
- Colour rendering index Ra≥80
- BC-B22d or ES-E27 cap
- Opal white finish
- Dimmable - DuoDim™ Technology compatible with both leading and trailing edge dimmers*
- For indoor use only

Product Code	Watts (W)	Volts (V)	Cap	Colour Appearance	Colour Temp (K)	Total Lumens (lm)	Incandescent Equivalent (W)	Dimensions (mm)	Energy Rating	Order Qty
G80 - Single Carton										
5471	7	240	BC-B22d	Warm White	2700	806	60	80 120	A++	1
5488	7	240	ES-E27	Warm White	2700	806	60	80 120	A++	1
G95 - Single Carton										
5495	9	240	BC-B22d	Warm White	2700	1055	75	95 130	A++	1
5501	9	240	ES-E27	Warm White	2700	1055	75	95 130	A++	1

* The lamp is compatible with most dimmer switches, please refer to following pages for up-to-date list of compatible dimmer switches.



BC-B22d Cap



ES-E27 Cap



Experts in lighting since 1878

LED G80/G95 Dimmable Opal Globe



The below table is designed to help you choose a suitable dimmer switch for your Crompton Lamp dimmable product. Crompton Lamps have extensively tested the below dimmer switches to evaluate their dimming function and to make sure the dimmer switch meets our dimming compatibility standards.

All compatible dimmer switches may require low end trimming.

For guidelines on dimmer switches not listed below, or for more information please contact Crompton Lamps.

Manufacturer	Dimmer Model	Dimmer Wattage	Dimmer Type	Lamps Tested Per Circuit	Notes
Aurora	AU-DSP401	60W-400W	Leading	1-5	Flickers below 30%
Aurora	AU-DSP651	75W-650W	Leading	1-5	Flickers below 30%
Aurora	AU-DSP400X	60W-400W	LED	1-5	Flickers 0-20%
Danlers	DSS1D 250W	40W-250W	Leading	1-3	Steps from 0-30%
Danlers	DP1D 400W1ET	60W-400W	Leading	1-5	Steps from 0-30%
Danlers	DPDLED	5W-250W	Leading	1-5	Steps from 0-30%
MK	K451 1xxxLV	40W-220W	Leading	1-5	Does not dim below 20%
MK	K1521WHILV	40W-300W	Leading	2-5	Does not dim below 30%
MK	K1524WHILV	40W-300W	Leading	1-5	Does not dim below 35%
Zano	ZANOMO500	11W-50W	Leading	1-5	Steps from 0-30%
Varilight	V-Pro JQP401W	10W-400W	Trailing	2-5	Does not dim below 50%
Varilight	V-Pro JQP252W	10W-250W	Trailing	2-5	Does not dim below 50%
Eaton	P9131	60W-250W	Leading	1-3	Steps from 0-20%
Eaton	P9141	60W-400W	Leading	1-5	Steps from 0-20%
Core	3010	60W-400W	Leading	1-5	Steps from 0-20%
Core	3011	60W-250W	Leading	1-3	Steps from 0-20%
Leviton	LEV71906MOD	75W-650W	Leading	1-5	Steps from 0-20%

The below list of dimmer switches have also been tested by Crompton Lamps and do not meet our dimming compatibility standards. Crompton Lamps does not recommend the use of any of the below dimmer switches as they may cause lamp/dimmer failure.

Danlers: DSS1D 400W, DQDGEU400W

Experts in lighting since 1878

Crompton Lamps Limited registered in England and Wales No. 05590551
Registered office and correspondence address: Unit 2, Martree Business Park, Bowling Back Lane, Bradford BD4 8QE

Tel: +44 (0)1274 657 088 **Fax:** +44 (0)1274 657 087 **Email:** sales@cromptonlamps.com **Web:** www.cromptonlamps.com

All images and specifications are for illustration purposes only and are subject to change without notice.
E. & O. E. © Crompton Lamps Limited 2017